



# COAX CABLESTRIPPER

## Short Description

Handy and comfortable StrippingTool

## Specifications

- Supported cable types: RG 11 and similar to 10.5 mm outside diameter
- 2 blades for the simultaneous stripping of the outer conductor and the inner conductor in one operation
- Both blades are adjusted precisely by means of the key supplied to the tool on different cable types
- Blade distance pres

## Properties

- Product Dimensions: 10.5 x 2.1 x 3.4 cm
- Weight: 20 g
- Colour: Black
- Package Quantity: 1



Connecting with quality!

# Instructions

## Instructions

1. Holding the tool, grooved edge upwards, between fingers and thumb, press down to open jaws.
2. Insert the coax cable into the left-hand side of the jaws until the cable reaches the edge of the "V" block on the right-hand side of the tool. Release the thumb to close the jaws.
3. Insert the index finger through the ring and turn the stripper clockwise 4-5 times.
4. Open jaws again and clean scraps away. Remove the cable and pull off the outer jacket and dielectric to expose the shield and centre conductor. The stripping operation is now complete.

## Adjustment of blades:

To adjust cutting dimensions snap the build-in hex key wrench and insert it into the appropriate hex socket to align the blades to fit your coax size. Turn clockwise to increase cutting depth and counter clockwise to decrease cutting depth.

